

IVO Voice alarm system

VCT – volume controls



They are designed to adjust the volume (damping) on the IVO loudspeaker lines. The VCT25R and VCT80R controllers require an additional pair of wires to activate the bypass relay.

VCT25: 25W load power, 3-wire speaker line

VCT80: 80W load power, 3-wire speaker line

VCT25R: load power 25W, loudspeaker and control line, 4-wire

VCT80R: 80W load power, loudspeaker and control line, 4-wire

Selected technical data

Speaker line	3-wire (VCT25, VCT80) 2-wire (VCT25R, VCT80R) +2 wires for activating the bypass relay
Mounting	Wall or concealed
Number of damping adjustment steps	10+disconnection
Housing colour	White
Dimensions	VCT25, VCT25R: 84x84x54 VCT80, VCT80R: 149x87x61